

## PP12

### Taps and splitters

2-output clamp splitter in TV band (47-862MHz).



### Technical Chars

- **Metal enclosure** with screw terminals for complete shielding.
- To make the system more robust, it is recommended to use a divider to split the signal and a TAP to directly serve the outlets.
- V.S.W.R. <1.2.

PP12		
Code		220370
Outputs		2
Output separation		
47-68MHz	dB	18
174-230MHz	dB	18
470-606 MHz	dB	18
606-862 MHz	dB	18
Specifications		
Insertion loss	dB	4
Dimensions and packaging		
Pieces		10
EAN code		8016978013807
Multiple EAN		8016978013814
Packaging dimensions	mm	170 x 75 x 45
Packaging weight	kg	0.48